

Europäisches Patentamt
European Patent Office
Office européen des brevets



(11) EP 0 964 596 A2

(12) EUROPEAN PATENT APPLICATION

(43) Date of publication:
15.12.1999 Bulletin 1999/50

12/15/99

(51) Int. Cl.⁶: H04Q 7/38

(21) Application number: 99110958.8

6/8/99

(22) Date of filing: 08.06.1999

(84) Designated Contracting States:
AT BE CH CY DE DK ES FI FR GB GR IE IT LI LU
MC NL PT SE
Designated Extension States:
AL LT LV MK RO SI

(72) Inventor: Tsumura, Soichi
Minato-ku, Tokyo (JP)

(74) Representative:
VOSSIUS & PARTNER
Siebertstrasse 4
81675 München (DE)


(30) Priority: 09.06.1998 JP 16072198

(71) Applicant: NEC CORPORATION
Tokyo (JP)

(54) Method of assigning frequency using propagation loss

(57) A process of assigning frequencies uses propagation loss in a CDMA communication system. A base station measures propagation loss over a channel between the base station and a mobile station. If the measured propagation loss is greater than a certain fixed value, the base station determines that since the mobile station is present in a position distant from the base station, the mobile station may possibly interfere with a base station of another CDMA communication system. The base station assigns a frequency channel which is not adjacent to the frequency band assigned to the other CDMA communication system to the mobile station.

Fig. 5



Best Available Copy

EP 0 964 596 A2

Description

[0001] The present invention relates to a method of assigning a frequency from a base station to mobile stations in a CDMA (Code Division Multiple Access) communication system.

[0002] The CDMA communication system are is expected to be the next-generation mobile communication system. The CDMA communication system is advantageous in that a plurality of adjacent base stations can share one frequency band.

[0003] In a CDMA communication system, different codes are assigned to respective channels, and signals are demodulated on the basis of the fact that there is a difference between autocorrelated values, which are correlated values between the same codes, and cross-correlated values, which are correlated values between different codes. It is therefore necessary that the cross-correlated values between the codes assigned to the respective channels are sufficiently lower than the autocorrelated values. It is most preferable that all the codes which are used be orthogonal to each other (the cross-correlated values be 0). However, since it is difficult for all the codes which are used by base stations that are adjacent to each other to be orthogonal to each other, the cross-correlated values are generally not 0.

[0004] If the cross-correlated values are not 0, then there is a possibility that when a mobile station A1 is present near a base station and a mobile station A2 is present far from the base station, depending on the ratio of transmission powers of the mobile stations A1, A2 at the time signals from the mobile stations A1, A2 arrive at the antenna of the base station, the correlated value (cross-corrected value) between the signal from the mobile station A1 and the code assigned to the mobile station A2 may be greater than the correlated value (autocorrelated value) between the signal from the mobile station A2 and the code assigned to the mobile station A2.

[0005] In such a case, because the cross-corrected value is not lower than the autocorrelated value, the signal from the mobile station A2 cannot properly be demodulated. This could lead to a fatally dangerous situation where if the signal power sent from one mobile station and received by the antenna of a base station is much greater than the signal power sent from another mobile station and received by the antenna of the base station, then the base station is unable to decode signals other than the signal from the mobile station whose reception power is larger at the antenna of the base station. This problem is widely known as a near-far problem. In order to solve the problem, it is necessary to perform a transmission power control process on transmitters for equalizing signal powers from all the transmitters in input signals received by a receiver.

[0006] If a mobile communication system is operated by a sole network operator and a handoff is properly carried out as a mobile station moves, then communica-

tions are effected via a path whose transmission loss is smallest between the base station and the mobile station. It is thus possible to perform a transmission power control process in order to minimize the transmission power of the mobile station for thereby solving the near-far problem.

[0007] Another problem occurs when a plurality of mobile communications are operated in one area by a plurality of network operators. In this situation, if the base stations are located at one site or mutual roaming is carried out between the different network operators, then no difficulty arises because a path whose transmission loss is smallest between base and mobile stations is practically selected. Since, however, such a solution is generally difficult to achieve, it has been customary to solve the above problem by assigning different frequency bands to the respective network operators, as shown in Fig. 1 of the accompanying drawings. Fig. 1 shows the assignment of four frequency channels to each of network operators A, B, C.

[0008] If the frequency bands assigned to the respective network operators are successive, then in frequency channels located at a boundary between different frequency bands, the leaking power in an adjacent channel of a transmission signal from a mobile station causes a near-far problem to a frequency channel of another network operator. For example, in frequency channels fa1, fa4 located at a boundary of the frequency band assigned to a network operator A, the leaking power in an adjacent channel of a transmission signal from a mobile station causes a near-far problem to a frequency channel fc4 of a network operator C and a frequency channel fb1 of a network operator B.

[0009] Fig. 2 of the accompanying drawings shows CDMA communication systems provided by a plurality of network operators and located in one area. As shown in Fig. 2, two network operators A, B provide respective CDMA communication systems in on area. The CDMA communication system provided by the network operator A has base stations (not shown) which communicate with mobile stations present in cells A1 - A7. It is assumed that the cells A1 - A7 overlap a cell B1 of a base station of the CDMA communication system provided by the network operator B, and that the frequency channels shown in Fig. 1 are assigned to each of the network operators A, B.

[0010] In Fig. 2, α represents the position of the base station of the cell A1, β represents the position of the base station of the cell B1, and γ represents the position of the base station of the cell A4.

[0011] In order to solve a near-far problem in one CDMA communication system, each of the base stations control the transmission powers of mobile stations linked thereto, and the reception powers at the antenna of each of the base stations are controlled at a constant level at all times irrespective of the positions of the mobile stations. Specifically, if the distance between a mobile station and a base station linked thereto is large,

then the transmission power of the mobile station is increased, and if the distance between a mobile station and a base station linked thereto is small, then the transmission power of the mobile station is reduced.

[0012] In Fig. 2, when a mobile station belonging to the CDMA communication system provided by the network operator A moves from the position α to the position β to the position γ , the transmission power of the mobile station is first progressively increased from a low level to a maximum level at the position β . Near the position β , a handoff takes place from the base station of the cell A1 to the base station of the cell A4. As the mobile station approaches the position γ , the transmission power of the mobile station is gradually lowered.

[0013] The transmission power of a mobile station in the cell A1 which uses the frequency channel fa4 changes as shown in Fig. 3a of the accompanying drawings. The reception power at the base station of the cell A1 in the position α and the reception power at the base station of the cell A4 in the position γ change as shown in Fig. 3b of the accompanying drawings.

[0014] As shown in Fig. 3b, when the mobile station is located between the position α and the position β , the reception power at the base station of the cell A1 is constant, and when the mobile station is located between the position β and the position γ , the reception power at the base station of the cell A1 is gradually reduced. The reception power at the base station of the cell A4 is gradually increased when the mobile station is located between the position α and the position β , and is constant when the mobile station is located between the position β and the position γ . When the reception powers are constant, the reception powers have the same level at the base stations of the cells A1, A4. At this time, the reception power in the frequency channel fb1 of the base station in the position β of the cell B1 of the network operator B is indicated by the solid-line curve in Fig. 3c of the accompanying drawings because of the leaking power in an adjacent channel from a mobile station. The conventional CDMA communication system has strict standards for the leaking power in an adjacent channel with respect to a transmitted signal from a mobile station, so that any interference which occurs with the base station of the cell when the mobile station is in the position β can be reduced to a level low enough not to cause practical problems to the CDMA communication system.

[0015] The reception power in the frequency channel fb1 in the base station of the cell B1 at the time the mobile station has a transmission frequency channel fa3 is indicated by the dotted-line curve in Fig. 3c. The reception power in the frequency channel fb1 is low because the leaking power is exponentially reduced as the reception frequency channel is away from the transmission frequency channel.

[0016] As described above, the conventional CDMA communication system has strict standards for the leaking power in an adjacent channel with respect to a

transmitted signal from a mobile station so as to solve the near-far problem. Therefore, the transmitters of the mobile stations, particularly the final-stage power amplifiers thereof, are required to have a high level of linearity, and hence have a large consumption power requirement and an increase in size.

[0017] It is an object of the present invention to provide a method of assigning a frequency from a base station to mobile stations in a CDMA communication system for solving a near-far problem without strict standards for the leaking power in an adjacent channel with respect to the transmitter of a mobile station and for reducing a consumption power requirement and size of base stations.

[0018] To achieve the above object, in a method of assigning a frequency in a CDMA communication system according to the present invention, a base station measures a propagation loss over a channel between the base station and a mobile station. If the measured propagation loss is greater than a certain fixed value, then the base station determines that since the mobile station is present in a position distant from the base station, the mobile station may possibly interfere with a base station of another CDMA communication system. The base station assigns a frequency channel which is not adjacent to the frequency band assigned to the other CDMA communication system, to the mobile station which may possibly interfere with a base station of another CDMA communication system. Therefore, it is possible to reduce interference with a base station belonging to another network operator, without strict standards for the leaking power in an adjacent channel of a transmitted signal of a mobile station. Therefore, the consumption power requirement and size of the transmitter of the mobile station can be reduced.

[0019] In another method of assigning a frequency in a CDMA communication system according to the present invention, a frequency channel which is not adjacent to the frequency band assigned to another CDMA communication system is assigned to a mobile station whose transmission power level is greater than a certain fixed value.

[0020] The above and other objects, features, and advantages of the present invention will become apparent from the following description when taken in conjunction with the accompanying drawings which illustrate preferred embodiments of the present invention by way of example.

Fig. 1 is a diagram showing the assignment of four frequency channels to each of network operators; Fig. 2 is a diagram showing cells of conventional CDMA communication systems provided by network operators A, B shown in Fig. 1; Fig. 3a is a graph showing the manner in which the transmission power of a mobile station changes in the conventional CDMA communication systems changes;

Fig. 3b is a graph showing the manner in which the reception powers in the base stations of cells A1, A4 in the conventional CDMA communication systems change;

Fig. 3c is a graph showing the manner in which the reception power in the frequency channel fb1 of the base station of a cell B1 in the conventional CDMA communication systems changes;

Fig. 4 is a diagram showing a CDMA communication system according to a first embodiment of the present invention;

Fig. 5 is a flowchart of a process of assigning a frequency in the CDMA communication system shown in Fig. 4;

Fig. 6 is a diagram showing cells of the CDMA communication system shown in Fig. 4;

Fig. 7 is a graph showing the manner in which the reception power in the frequency channel fb1 of the base station of a cell B1 in the CDMA communication system shown in Fig. 4 changes; and

Fig. 8 is a flowchart of a process of assigning a frequency in a CDMA communication system according to a second embodiment of the present invention.

1st Embodiment:

[0021] As shown in Fig. 4, a CDMA communication system according to a first embodiment of the present invention has a mobile station 10 and a pair of base stations 20, 21. The base station 20 communicates with mobile stations in a cell A4, and the base station 21 communicates with mobile stations in a cell A1. For example, the mobile station 10 moves in the cell A4, and hence communicates with the base station 20.

[0022] A process of assigning a frequency in the CDMA communication system shown in Fig. 4 will be described below with reference to Fig. 5.

[0023] At first, in step 101, value 1 and value 2 are set to V_0 . In step 102, a base station measures a propagation loss in a channel established between the base station and each of the mobile stations. The base station can obtain a propagation loss by calculating the difference between a transmission power level of each of the mobile stations, which transmission power level is reported therefrom, and a reception power level of a signal received from each of the mobile stations by the base station. The base station can also obtain a propagation loss by calculating the difference between a reception power level of a signal received from the base station by each of the mobile stations, which reception power level is reported from the mobile station, and a transmission power level of the base station for each of the mobile stations.

[0024] In step 103, the base station decides whether the propagation loss with respect to a mobile station is greater than value 1 or not. If the propagation loss is greater than value 1 in step 103, then the base station

assigns a frequency channel which is not adjacent to a frequency channel assigned to another CDMA communication system, to the mobile station in step 105. If the propagation loss is equal to or smaller than value 1 in step 103, the base station decides whether the propagation loss with respect to a mobile station is equal to or smaller than value 2 or not in step 104. If the propagation loss is greater than value 2 in step 104, the process is forwarded to step 103.

[0025] If the propagation loss is equal to or smaller than value 2 in step 104, then the base station preferentially assigns a frequency channel which is adjacent to a frequency channel assigned to another CDMA communication system, to the mobile station in step 106. Finally, in step 107, value 1 is set to V_1 and value 2 is set to V_2 , then process is forwarded to step 102.

[0026] The process of assigning a frequency in the CDMA communication system will be described in specific detail below with reference to Fig. 6.

[0027] As described above, the base station measures a propagation loss in a channel established between the base station and each of the mobile stations. Based on the measured propagation loss, the base station divides the mobile stations present in its own area into a plurality of groups. In Fig. 6, the mobile stations are divided into two groups. While the mobile stations are shown as being grouped based on their positions in Fig. 6, the mobile stations are actually grouped based on the propagation losses.

[0028] In Fig. 6, the mobile stations in the cell A1 are divided into a group A1₁ and a group A1₂, and the mobile stations in the cell A4 are divided into a group A4₁ and a group A4₂. The mobile stations whose propagation losses are equal to or smaller than a value are classified into the group A1₁ or A4₁, and the mobile stations whose propagation losses are greater than the value are classified into the group A1₂ or A4₂.

[0029] The mobile stations belonging to the groups A1₂, A4₂ are assigned a frequency channel fa2 or fa3 in Fig. 1 which is not adjacent to a frequency channel assigned to another network operator from among the frequency channels assigned to the CDMA communication system. The mobile stations belonging to the groups A1₁, A4₁ are preferentially assigned a frequency channel fa1 or fa4 which is adjacent to a frequency channel assigned to another network operator.

[0030] In the CDMA communication system according to the present embodiment, when a mobile station moves from a position a to a position y, the following frequency channel assignment is performed.

[0031] When the mobile station is in the position a, the base station of the cell A1 handles the mobile station as belonging to the group A1₁, and preferentially assigns the frequency channel fa1 or fa4 to the mobile station. When the mobile station moves and its propagation loss becomes greater than the value, the base station of the cell A1 classifies the mobile station into the group A1₂, and changes the frequency channel being used to fa2

freq. Assigning
different
groups,
different
operators

while
moving
function
of distance
or position

or fa3. When the mobile station further moves to the position β , a handoff occurs from the base station of the cell A1 to the base station of the cell A4. At this time, the frequency channel being used is not changed and base station of the cell A4 handles the mobile station as belonging to group A4₂. When the mobile station further moves and its propagation loss as measured by the base station of the cell A4 becomes lower than the value, the base station of the cell A4 handles the mobile station as belonging to the group A4₁, and preferentially changes the frequency channel being used to fa1 or fa4.

[0032] The above frequency channel assignment, as shown in Fig.7, makes it possible to reduce an upper limit for the reception power in the frequency channel fb1 in the base station of a cell B1 of a network operator B at the position β , to a level lower than the interference power indicated by the solid-line curve in Fig. 3c.

2nd Embodiment:

[0033] In the first embodiment, a group to which a mobile station belongs is determined on the basis of a propagation loss over a channel with the mobile station, as measured by the base station. According to the second embodiment, a group to which a mobile station belongs is determined on the basis of the transmission power level of the mobile station, rather than a propagation loss. According to a transmission power control process carried out on the mobile station by the base station, the transmission power of the mobile station is controlled so as to be greater if the propagation loss is greater, and the transmission power of the mobile station is controlled so as to be smaller if the propagation loss is smaller. Therefore, the second embodiment can offer the same advantages as the first embodiment even though it employs the transmission power level of the mobile station.

[0034] A process of assigning a frequency in the CDMA communication system according to the second embodiment will be described below with reference to Fig. 8.

[0035] At first, in step 601, value 1 and value 2 are set to V_0 . In step 602, a base station receives a transmission power level from a mobile station. The base station decides whether the transmission power level is greater than value 1 or not in step 603. If the transmission power level is greater than value 1 in step 603, then the base station assigns a frequency channel which is not adjacent to a frequency channel assigned to another CDMA communication system, to the mobile station in step 605. If the transmission power level is equal to or smaller than value 1 in step 603, the base station decides whether the transmission power level is equal to or smaller than value 2 or not in step 604. If the transmission power level is greater than value 2 in step 604, then the process is forwarded to step 603.

[0036] If the transmission power level is equal to or smaller than value 2 in step 604, then the base station

preferentially assigns a frequency channel which is adjacent to a frequency channel assigned to another CDMA communication system, to the mobile station in step 606. Finally, in step 607, value 1 is set to V_1 and value 2 is set to V_2 , then process is forwarded to step 602.

[0037] In the first and second embodiments described above, the mobile stations in one cell are divided into two groups. However, the principles of the present invention are also applicable to CDMA communication systems where the mobile stations in one cell are divided into more than two groups.

[0038] Although certain preferred embodiments of the present invention have been shown and described in detail, it should be understood that various changes and modifications may be made therein without departing from the scope of the appended claims.

Claims

1. A method of assigning frequencies in CDMA communication systems providing services in the same area when different frequency bands are assigned to each CDMA communication system in which a base station of one of the CDMA communication systems selects a frequency channel to be used from the assigned frequency band and assigns the selected frequency channel to a mobile station, comprising the steps of:

measuring a propagation loss over a channel between said base station and a mobile station present in a cell of said base station;
 assigning a frequency channel which is not adjacent to the frequency band assigned to another CDMA communication systems from among the frequency channels assigned to said CDMA communication systems to a mobile station whose propagation loss is greater than a first value; and
 preferentially assigning a frequency channel which is adjacent to the frequency band assigned to another CDMA communication systems from among the frequency channels assigned to said CDMA communication systems to a mobile station whose propagation loss is equal to or smaller than a second value.

2. A method according to claim 1, wherein said step of measuring a propagation loss comprises the step of:

measuring said propagation loss based on the difference between the transmission power level of a mobile station reported to said base station and the reception power level of the signal transmitted from said mobile station and received at said base station.

3. A method according to claim 1, wherein said step of measuring a propagation loss comprises the step of:

measuring said propagation loss based on the difference between the reception power level at the mobile station of a signal from said base station reported from said mobile station to said base station and the transmission power level of said base station to the mobile station.

4. A method of assigning frequencies in CDMA communication systems providing services in the same area when different frequency bands are assigned to each CDMA communication system in which a base station of one of the CDMA communication systems selects a frequency channel to be used from the assigned frequency band and assigns the selected frequency channel to a mobile station, comprising the steps of:

indicating the transmission power level of each mobile station from the mobile station to a base station respectively;
 assigning a frequency channel which is not adjacent to the frequency band assigned to another CDMA communication systems from among the frequency channels assigned to said CDMA communication system, to a mobile station whose transmission power level is greater than a first value; and
 preferentially assigning a frequency channel which is adjacent to the frequency band assigned to another CDMA communication system from among the frequency channels assigned to said CDMA communication system to a mobile station whose transmission power level is equal to or smaller than a second value.

5. A CDMA communication system comprising:

at least one mobile station; and
 a plurality of base stations for measuring a propagation loss over a channel with a mobile station present in a cell thereof, assigning a frequency channel which is not adjacent to the frequency band assigned to another CDMA communication system which provides services in the same area as the CDMA communication system from among the frequency channels assigned to said CDMA communication system to a mobile station whose propagation loss is greater than a first value; and
 preferentially assigning a frequency channel which is adjacent to the frequency band assigned to the other CDMA communication systems from among the frequency channels assigned to said CDMA communication sys-

tem, to a mobile station whose propagation loss is equal to or smaller than a second value.

6. A CDMA communication system according to claim 5, wherein each of said mobile stations comprises means for measuring said propagation loss based on the difference between the transmission power level of a mobile station reported from said mobile station to said base station and the reception power level of the signal transmitted from said mobile station and received at said base station.

7. A CDMA communication system according to claim 5, wherein each of said mobile stations comprises means for measuring said propagation loss based on the difference between the reception power level at the mobile station of a signal from said base station reported from said mobile station to said base station and the transmission power level of said base station to the mobile station.

8. A CDMA communication system comprising:

at least one mobile station for indicating a transmission power level to a base station; and
 a plurality of base stations for assigning a frequency channel which is not adjacent to the frequency band assigned to another CDMA communication system which provides services in the same area as the CDMA communication system from among frequency channels assigned to the CDMA communication system to a mobile station whose transmission power level is greater than a first value, and preferentially assigning a frequency channel which is adjacent to the frequency band assigned to the other CDMA communication system from among the frequency channels assigned to said CDMA communication system to a mobile station whose transmission power level is equal to or smaller than a second value.

Fig. 1

PRIOR ART




Fig. 2
PRIOR ART




Fig. 3 a
PRIOR ART




Fig. 3 b
PRIOR ART




Fig. 3 c
PRIOR ART




Fig. 4




Fig. 5




Fig. 6




Fig. 7






Fig. 8





Europäisches Patentamt
European Patent Office
Office européen des brevets



(11) EP 0 964 596 A3

(12) EUROPEAN PATENT APPLICATION

(88) Date of publication A3:
13.09.2000 Bulletin 2000/37

(51) Int. Cl.⁷: H04Q 7/38

(43) Date of publication A2:
15.12.1999 Bulletin 1999/50

(21) Application number: 99110958.8

(22) Date of filing: 08.06.1999

(84) Designated Contracting States:
AT BE CH CY DE DK ES FI FR GB GR IE IT LI LU
MC NL PT SE
Designated Extension States:
AL LT LV MK RO SI

(72) Inventor: Tsumura, Soichi
Minato-ku, Tokyo (JP)

(74) Representative:
VOSSIUS & PARTNER
Siebertstrasse 4
81675 München (DE)


(30) Priority: 09.06.1998 JP 16072198

(71) Applicant: NEC CORPORATION
Tokyo (JP)

(54) Method of assigning frequency using propagation loss

(57) A process of assigning frequencies uses propagation loss in a CDMA communication system. A base station measures propagation loss over a channel between the base station and a mobile station. If the measured propagation loss is greater than a certain fixed value, the base station determines that since the mobile station is present in a position distant from the base station, the mobile station may possibly interfere with a base station of another CDMA communication system. The base station assigns a frequency channel which is not adjacent to the frequency band assigned to the other CDMA communication system to the mobile station.

Fig. 5



EP 0 964 596 A3



European Patent
Office

EUROPEAN SEARCH REPORT

Application Number
EP 99 11 0958

DOCUMENTS CONSIDERED TO BE RELEVANT			
Category	Citation of document with indication, where appropriate, of relevant passages	Relevant to claim	CLASSIFICATION OF THE APPLICATION (Int.Cl.6)
X	EP 0 544 095 A (MOTOROLA INC) 2 June 1993 (1993-06-02)	1-3,5-7	H04Q7/38
A	* column 2, line 41 - column 3, line 2 *	4,8	
X	EP 0 782 361 A (AT & T CORP) 2 July 1997 (1997-07-02)	4,8	
A	* page 10, line 26 - page 12, line 19 *	1-3,5-7	
			TECHNICAL FIELDS SEARCHED (Int.Cl.6)
			H04Q
The present search report has been drawn up for all claims			
Place of search THE HAGUE		Date of completion of the search 21 July 2000	Examiner Weinmiller, J
<p>CATEGORY OF CITED DOCUMENTS</p> <p>X : particularly relevant if taken alone Y : particularly relevant if combined with another document of the same category A : technological background O : non-written disclosure P : intermediate document</p> <p>T : theory or principle underlying the invention E : earlier patent document, but published on, or after the filing date D : document cited in the application L : document cited for other reasons & : member of the same patent family, corresponding document</p>			

EPO FORM 1500 03.02 (P04001)

**ANNEX TO THE EUROPEAN SEARCH REPORT
ON EUROPEAN PATENT APPLICATION NO.**

EP 99 11 0958

This annex lists the patent family members relating to the patent documents cited in the above-mentioned European search report.
The members are as contained in the European Patent Office EDP file on
The European Patent Office is in no way liable for these particulars which are merely given for the purpose of information.

21-07-2000

Patent document cited in search report	Publication date	Patent family member(s)	Publication date
EP 0544095 A	02-06-1993	DE 69230716 D US 5708969 A	06-04-2000 13-01-1998
EP 0782361 A	02-07-1997	US 5787352 A JP 9200843 A	28-07-1998 31-07-1997

EPO FORM P0458

For more details about this annex : see Official Journal of the European Patent Office, No. 12/82

**This Page is Inserted by IFW Indexing and Scanning
Operations and is not part of the Official Record**

BEST AVAILABLE IMAGES

Defective images within this document are accurate representations of the original documents submitted by the applicant.

Defects in the images include but are not limited to the items checked:

- ☐ BLACK BORDERS
- ☐ IMAGE CUT OFF AT TOP, BOTTOM OR SIDES
- ☐ FADED TEXT OR DRAWING
- ☒ BLURRED OR ILLEGIBLE TEXT OR DRAWING
- ☐ SKEWED/SLANTED IMAGES
- ☐ COLOR OR BLACK AND WHITE PHOTOGRAPHS
- ☐ GRAY SCALE DOCUMENTS
- ☐ LINES OR MARKS ON ORIGINAL DOCUMENT
- ☐ REFERENCE(S) OR EXHIBIT(S) SUBMITTED ARE POOR QUALITY
- ☐ OTHER: _____

IMAGES ARE BEST AVAILABLE COPY.

As rescanning these documents will not correct the image problems checked, please do not report these problems to the IFW Image Problem Mailbox.